



Drugi wyzwalacz wzrostowy do IZMX16/40 230 VAC/DC

Typ
Catalog No.
Alternate Catalog No.

+IZMX-STS230AD-1
184279
67C2820G52

Program dostaw

Asortyment			Akcesoria
Akcesoria			Zdalne sterowanie
Akcesoria			Drugi wyzwalacz wzrostowy
			Tylko w połączeniu z „pierwszym” wyzwalaczem wzrostowym. Nie może być łączone z wyzwalaczem podnapięciowym.
maksymalna częstotliwość załączania	załączenia/ min		3
			jest ograniczony do 3/min ze względu na wysoki prąd przyciągania w ciągu 35 ms. Zachować częstotliwość załączania łącznika = 60/h
Napięcie sterownicze pomiaru	U _s	V	208 - 240 V AC 50/60 Hz 208 - 250 V DC
Zakres pracy	x U _s	Współczynnik	0,7 - 1,1
maks. prąd trzymania	I _n	A	0.034
maks. moc trzymania	AC/DC	VA/W	9
Maks. moc przyciągania (35 ms)	AC/DC	VA/W	0
Całkowity czas przełączania łącznika mocy	@ U _s =100%	ms	30 (IZMX16..., INX16...) 35 (IZMX40..., INX40...)
Stosowane do			IZMX16..., IZMX40... INX16..., INX40...

Świadectwo typu zgodnie z IEC/EN 61439

Dane techniczne dla zaświadczenia rodzaju konstrukcji			
Robocza temperatura otoczenia min.		°C	-25
Robocza temperatura otoczenia maks.		°C	70

Dane techniczne zgodne z ETIM 6.0

Low-voltage industrial components (EG000017) / Shunt release (for power circuit breaker) (EC001023)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Full load current trip (ecl@ss8.1-27-37-04-18 [AKF016010])			
Rated control supply voltage U _s at AC 50HZ		V	208 - 240
Rated control supply voltage U _s at AC 60HZ		V	208 - 240
Rated control supply voltage U _s at DC		V	220 - 250
Voltage type for actuating			AC/DC
Initial value of the undelayed short-circuit release - setting range		A	0
End value adjustment range undelayed short-circuit release		A	0
Type of electric connection			Flat plug-in connection
Number of contacts as normally open contact			0
Number of contacts as normally closed contact			0
Number of contacts as change-over contact			0
Suitable for power circuit breaker			Yes
Suitable for off-load switch			Yes
Suitable for motor safety switch			No
Suitable for overload relay			No