

PV switch disconnector

The construction of the switch ensures reliable switching up to 58A with 1000V in the category DC 21B.

The construction of the contacts and the material selection guarantee that no oxidation (small switching frequency developes, and is thus prevented inadmissible heating-up.

The switch disconnector has 2, 4 or 4+2 contacts, by serial / parallel wirring of the contacts the contact rating will be increased.

The switching speed at the manually operated handle does not have an effect on the switching attitude of the contacts.





General characteristics	
Rated voltage	Up to 1000V d.c.
Rated current	Up to 58A d.c.
Standards	IEC 60364-7-712
Application	For interupting the DC/AC inverter from the solar panels


PV switch disconnector for photovoltaic								
Code	Туре		Weight [g]	Packaging [pcs]				
004660060	LS16 SMA A2		- 150	1				
004660061	LS25 SMA A2	2-pole						
004660062	LS32 SMA A2							
004660063	LS16 SMA A4							
004660064	LS25 SMA A4	4-pole						
004660065	LS32 SMA A4							
004660066	LS32 SMA A4+2	4+2 pole	430					
004660067*	LSV-B1							

Switch disconnectors "LS.." are switch gears for interupting DC/AC-inverter from the solar-panels. Photovoltaic-installations have to be equipped with DC-isolators according to IEC 60364-7-712.

^{*}Insulated Jumper







LS32 A4+2

Switch disconnectors and load switches for DC applications										
			DC 21B				DC 22B			
Technical data according to IEC 60947-3, VDE0660		500V	600V	800V	1000V	500V	600V	800V	1000V	
LS16	1 2_	2 poles in series	16A	16A	16A	9A	7A	5,5A	2A	1A
	1 2 3 4	4 poles in series	16A	16A	16A	16A	16A	16A	11,5A	8A
LS25	1 2	2 poles in series	25A	25A	20A	11A	8A	6A	2,5A	1,5A
	1 2 3 4	4 poles in series	25A	25A	25A	25A	25A	25A	12A	9A
L532		2 poles in series	32A	32A	23A	13A	9A	6,5A	3A	2A
	1 2 3 4	4 poles in series	32A	32A	32A	32A	32A	27,5A	12,5A	10A
LS32A4+2	1 3 5 7 1 3 5 7	4 poles in series +2 poles parallel	58A	58A	58A	58A	1	/	/	/

Because of very high breaking point capacity, switch disconnectors "LS..." are suitable for many different operating conditions.